Dialing From DMCC-SECRET (S)

To DMCC-S/VoSIP/ECVoIP

Dial 10-digit number: NYX-NNX-XXXX

To DRSN

Dial 10-digit number: 312-NNX-XXXX

To CDRSN

Dial 10-digit number: 312-84N-XXXX
(N=2 (Ottawa), N=3 (Winnipeg), N=4 (Halifax), 5(Esquimalt))

To SCIP Device (STE, etc.) VIA ECTOCRYP

DMCC dials "701" (access code), + DSN or commercial access code (DSN=94, CML=98), + the number of the SCIP Device followed by the "#" sign (terminator):

DSN Example: 701943128821234#
CML Example: 701987039411234#

To SCIP Device (STE, etc.) VIA DRSN CEU

User dials "700" (access code), + DSN or commercial access code (DSN=94, CML=98), + the number of the SCIP Device followed by the "#" sign (terminator):

1. 70094 plus DSN number #
2. 70098 plus Commercial number #
3. Called Party answers
4. IVR: "Go Secure"
5. Called Party "Goes Secure"
6. CEU attempts "key negotiation'
7. After successful negotiation parties connected.

example: 700943128821234#
example: 700983018821234#

To CMS (SECRET)

Dial 202-2 + 6-digit number with the following format: 202-2XX-XXXX Note: Calling any CMS at the Secret level is supported by replacing the first number in the prefix with a 2, example:

202-4XX-XXXX would be 202-2XX-XXXX
202-9XX-XXXX would be 202-2XX-XXXX

Dialing From DMCC-SECRET (S)

To UK DFTS SSS

Dial 205 + the appropriate UK DFTSSSS end user phone number:

SkyNet 5 Secure	205814XXXXXXXXXXXXX
UCCS	20580XXXXXX
Bahrain	2058336016XXXXX
SkyNet 5 Secure (CA)	2058336XXXXXXXX
Creech – Diego	205833[78][16]XXX
SONATA	20590XXXXXX
Synergy – Ship Secure	2059[17]XXXXXXX
Cormorant	20593XXXXXXXXXXXXX
Promina	20596XXXX
SSS Secure Operator	205981XXX
BRENT Gateway	20598[3456]XXXXXXXX
TMS	20599XXX
PLT	20583360745XXXX

To AUS DSN UC/VoIP

Dial a 14-digit number of the form:
610-61-N-XXXX-XXXX, where N= 2, 3, 4, 6, 7, 8, or 9

To NZL

Dial a 14--digit number of the form: 610-64-XXX-XXX-XXX

To IC and FBI

Dial 201 + 7-digit Intelligence Community Secure Telephone Network (ISTN) number

Dial 401 + 7 digit FBI number